



Product number : HR11E

Key Features

- Arms and disarms any X10 Security System
- Controls 16 different lamp or appliance modules.
- Features a "Panic" button for instant alarm
- Uses full 16 bit Code for RF transmission

Benefits

HR11E sends radio frequency signals to any X10 security console.

Can arm and disarm your X10 security system with a single button on the remote control : 2 arm buttons let you arm it with the motion detectors (MS17E) when you are away, and without them for when you return home. A slide switch allows you to arm your system with or without the siren in the "ready" state.

Can control up to 16 other devices:

On and Off lights and appliances connected to the Automation modules throughout the home (address 1 to 4 and 8 to 12).

Brighten and dim incandescent lamps connected to the Automation modules (address 1 to 4 and 8 to 12).

A panic button allows you to activate the alarm with or

Technical data

- Batteries: 4 x AAA
- Operating life: 1 year using all batteries
- RF frequency: 433,92 MHz
- Radiated output: < 1mW
- RF operating range: 30 m (open field)
- Code for RF transmission: 16 bit
- Approvals: EN 300 220-3 - EN 300 489-3 - CE (R&TTE)
- Ambient temperature:
 - 10°C to + 50° C (operation)
 - 20° C to + 70° C (storage)
- Dimensions:
72 x 115 x 20 mm
(width x height x depth)