



# Mini-Timer

## 4 Channel Timer / Controller



**Product number : MT10E**

### Benefits

The Mini-Timer controls four light or appliance modules, turning each one on or off up to twice a day at the time you choose.

With the Mini-Timer you can wake up to hot coffee, turn on a heater, switch off children's lights at bedtime, or come home to a lighted entrance.

The Mini-Timer also incorporates a special security function that you can use when you are away. This function randomly adjusts switching times by up to 30 minutes each side of the set time, so your home looks convincingly "lived-in"- a highly effective intruder deterrent.

The Mini-Timer allows you to turn on and off up to 8 modules instantly by pressing any of the four on/off rocker keys after setting the 1-4/5-8 slide switch to the desired position. You can also dim and brighten lights connected to lamp modules, DIN dimmer modules and wall dimmer modules at the touch of a button.

### Key Features

- Independent on/off timer control of four groups of X10 modules.
- Security random lamp switching function.
- Buttons to turn on/off and dim 8 light or appliance modules.
- 230V ~ 50Hz with battery backup (9 V).

### Technical data

- Supply voltage: 230V  $\pm$ 10% 50 Hz
- Battery: 9V 6LR61
- EMC emission: according to EN 50065-1
- EMC immunity: according to EN 50082-1
- Electrical safety: according to EN 60950 and EN 60065
- X-10 Powerline:  
120 kHz  $\pm$  2 kHz / 2,5 Vpk-pk
- Ambient temperature:
  - 10° C to + 50° C (operation)
  - 20° C to + 70° C (storage)
- Dimensions: 136 x 53 x 85 mm  
(width x height x depth )